

COMPRESSOR DATA SHEET

Federal Uniform Test Method for Certain Air Compressors Not Applicable

Rotary Compressor: Variable Frequency Drive

MODEL DATA - FOR COMPRESSED AIR

1	Manufacturer: Atlas Copco		
2	Model Number: ZR 315 VSD+-10.4	Date: 01-06-2024	
	<input type="checkbox"/> Air-cooled <input checked="" type="checkbox"/> Water-cooled	Type: Screw	
	<input type="checkbox"/> Lubricated <input checked="" type="checkbox"/> Oil-free	# of Stages: 2	
3	Full Load Operating Pressure*(b)	125.0	psig*(b)
4	Drive Motor Nominal Rating	214.6 & 214.6	hp
5	Drive Motor Nominal Efficiency	97.5 & 97.5	percent
6	Fan Motor Nominal Rating (if applicable)	--	hp
7	Fan Motor Nominal Efficiency	--	percent
8*	Input Power (kW)	Capacity (acfm) *(a,d)	Specific Power (kW/100 acfm)*(d)
	334.9 Max	1,868.2	17.9
	274.2	1,535.6	17.9
	217.5	1,203.0	18.1
	164.7	870.4	18.9
	113.3 Min	537.8	21.1
9*	Total Package Input Power at Zero Flow*(c,d)	0.0	kW
10			

*For models that are tested in the CAGI Performance Verification Program, these items are verified by program administrator

Consult CAGI website for a list of participants in the third party verification program:

www.cagi.org

Notes:

- Measured at the discharge terminal point of the compressor package in accordance with ISO 1217, Annex E; acfm is actual cubic feet per minute at inlet conditions.
- The operating pressure at which the Capacity and Electrical Consumption were measured for this data sheet.
- No Load Power. In accordance with ISO 1217, Annex E, if measurement of no load power equals less than 1%, manufacturer may state "not significant" or "0" on the test report.
- Tolerance is specified in ISO 1217, Annex E, as shown in table below:
NOTE: The terms "power" and "energy" are synonymous for purposes of this document.

Member



Volume Flow Rate at specified conditions		Volume Flow Rate	Specific Energy Consumption	No Load / Zero Flow Power
m ³ / min	ft ³ / min	%	%	
Below 0.5	Below 15	+/- 7	+/- 8	+/- 10
0.5 to 1.5	15 to 50	+/- 6	+/- 7	
1.5 to 15	50 to 500	+/- 5	+/- 6	
Above 15	Above 500	+/- 4	+/- 5	